

## Low-Cost, Portable, USB/ Ethernet Data Logger System

**16 Single-ended, 8  
Differential Analog Inputs**

**Stand-alone Data Logger  
Option Allows Data to be  
Saved to SD**

**Multiple Hardware Options**



Front of DI-710

The DATAQ Instruments DI-710 Series of products is a family of instruments for general purpose and stand-alone data logger data acquisition applications. Options include interface type, input voltage range, and PC-connected or stand-alone data logger operation. Interface options are USB or Ethernet. Gain ranges have selectable factors per channel of 1, 2, 4, and 8, or 1, 10, 100, and 1000. Instruments with the stand-alone data logger option feature a built-in multimedia socket that accepts standard Secure Digital (SD) memories to which acquired data may be stored without a connected PC. SD memories are the same commonly available mass storage devices used with digital cameras and MP3 players. Memories ranging in size from 16 MB to 1 GB are supported. Instruments without this option must remain tethered to a PC's USB or Ethernet port during data acquisition and use the PC's own program and memory to store acquired data.

All DI-710 Series products feature 14-bit measurement resolution, sixteen analog input channels that may be configured for single ended or differential operation per channel, and an 8-bit digital bi-directional port. PC-connected instruments stream data to the PC from as low as 0.048 Hz up to as high as 4,800 Hz throughput rate. Stand-alone data loggers store to their SD memory from as low as 0.0017 Hz up to as high as 14,400 samples per second. All DI-710 instruments are supplied with two removable, 16-position screw terminal access connectors.

## Features

### Stand-alone Data Logger Operation

Use a Secure Digital Card to record and store data—up to 1GB. A FIFO memory configuration allows the DI-710 to record continuously using a circular buffer approach. A push button allows manual start/stop control over the recording process. A multi color LED shows instrument status (Record, Standby, Busy, Error).

### Wide Signal Measurement Range

Suitable for use with all types of transducers, the 16-channel single-ended, 8-channel differential DI-710 features a per-channel measurement range of  $\pm 10$  V over four gain ranges. This allows you to simultaneously measure a wide range of signals with ease.

### Flexible Programmability

Channel-by-channel software selection of gain and single-ended/differential operation.

### High Throughput Rate

Supports sample throughput rates up to 4800 samples/sec to PC (depending on host computer speed) or up to 14400 samples/sec to memory card (stand-alone data loggers).

### High Resolution

14-bit resolution analog to digital conversion provides a responsive instrument capable of registering changes as small as one part in 8.192 ( $\pm 0.012\%$  of the full scale measurement range).

### File Protection

When powered down unexpectedly, the DI-710 Stand-alone model retains all data saved to its memory card.

### Easy to Connect & Use

Installs in seconds. Simply connect to your computer's USB port or to an Ethernet port. Connect power, then connect your signals to the provided screw terminal blocks (16 ports each). Stand-alone data loggers just require a Secure Digital Card and power.

### Includes Software

Be up and running minutes out of the box with WINDAQ software. WINDAQ/Lite Recording and Playback software is included free with the purchase of every DI-710 instrument. Record at rates up to 1000 Hz using WINDAQ/Lite Acquisition software. WINDAQ/Pro High Speed option allows you to record data as fast as your data acquisition system will allow. Use WINDAQ/Lite Playback software (WWB) to review, measure, and analyze your data during or after a recording session.

DATAQ Instruments Hardware Manager Software allows you to effectively manage and run multiple units installed to your PC, your network, or even over the Internet. It includes configuration software for stand-alone data loggers allowing a complete data acquisition configuration to be designed and downloaded from any local or remote PC. Upload software allows you to read data stored to an SD card over the DI-710's Ethernet interface.

# DI-710 Specifications

## Analog Inputs

**Number of Channels:** 16  
**Channel Configuration:** 16 single-ended; 8 differential; programmable per channel

## Measurement range, Accuracy, and Resolution

PGL models:	Gain	Range	Accuracy	Resolution
	1	±10V	±.25%FSR	±1.22mV
	10	±1V	±.25%FSR	±122µV
	100	±100mV	±.25%FSR	±12.2µV
	1000	±10mV	±.25%FSR	±1.22µV
PGH models:				
	1	±10V	±.25%FSR	±1.22mV
	2	±5V	±.25%FSR	±610µV
	4	±2.5V	±.25%FSR	±305µV
	8	±1.25V	±.25%FSR	±153µV

**Input Impedance, single-ended:** 1MΩ  
**Input impedance, differential:** 1MΩ each input to common  
**Input bias current:** 10µA for a 10V input, single channel  
**Input offset voltage:** Auto-zero  
**Input offset current:** 2nA (single channel)  
**Max. normal mode voltage:** 30V DC or peak AC  
**Max. common mode voltage:** 30V DC or peak AC  
**Common mode rejection:** 80db, gain=1, 1KΩ unbalance  
**Channel-to-channel crosstalk rejection:** -75db @ 100Ω unbalance  
**Gain temperature coefficient:** 50 ppm/°C  
**Offset temperature coefficient:** 0.25µV/°C  
**Digital filtering:** Standard: Conditional over-sampling  
 Stand-alone: None

## A/D Characteristics

**Type:** Successive approximation  
**Resolution:** 14-bit  
**Monotonicity:** ±2 LSB  
**Conversion Time:** 69µs

## Scanning Characteristics

**Max. throughput sample rate:** Standard: 4,800 Hz  
 Stand-alone: 14,400 Hz\*\*

\*When acquiring more than one channel at a gain of 100 max throughput is 7200 Hz;  
 When acquiring more than one channel at a gain of 1000 max throughput is 900 Hz.  
 \*\*Assumes SD memory latencies of 80 milliseconds or less.

**Min. throughput sample rate:** Standard: 0.0034 Hz  
 Stand-alone: 0.0017 Hz

**Max. scan list size:** 17 entries  
**Sample buffer size:** 2kb

## Controls (Stand-alone models)

**Single push-button:** Manual control Record and Standby

## Calibration

**Calibration cycle:** One year  
**Calibration method:** Automated Calibration Software, provided.

## Digital I/O

**Bits:** 8 bidirectional bits  
**Configuration:** Each bit is programmable as Input or Output  
**Output voltage levels:** Min. "1" 3V @ 2.5mA sourcing  
 Max. "0" 0.4V @ 2.5mA sinking  
**Output current:** Max. source, -2.5 mA; Max. sink, 2.5mA  
**Input voltage levels:** Min. required "1" 2V; Max allowed "0" 0.8V

## Ethernet Interface

**Type:** 10/100Base-T  
**Connector:** RJ-45  
**Protocol:** TCP/IP  
**Server Type:** DHCP

## Removable Memory (Stand-alone models)

**Type:** SD (Recommended: SanDisk SD Card)  
**Capacity:** 16 Mb to 1 Gb

## Real Time Clock (Stand-alone models)

**Type:** Date, hour, minute, second  
**Resolution:** 1 second  
**Accuracy:** 20 ppm

## Indicators

**Stand-alone models:** Three-color LED indicating Record, Standby, and Error conditions  
**Standard models:** Power LED

## Transfer Rate to PC

**Real Time:** up to 4,800 samples per second  
**From Memory Card:** up to 2,400 samples per second (Ethernet only)

## General

**Panel indicators:** Mode LED  
**Panel Controls:** Control push button (Stand-alone models)  
**Panel Slots:** Accepts SD-type flash memory  
**Input connectors:** Two, removable sixteen position terminal blocks  
**Operating Environment:** 0°C to 70°C  
**Enclosure:** Aluminum base with steel wrap-around. Aluminum end-panels with plastic bezels.  
**Dimensions:** 5<sup>7</sup>/<sub>16</sub>"D × 4<sup>1</sup>/<sub>8</sub>"W × 1<sup>1</sup>/<sub>2</sub>"H  
 13.81D × 10.48W × 3.81H cm.  
**Weight:** 14 oz.  
**Power Requirements:** USB: 9 to 36 VDC, 2 watts max  
 Ethernet: 9 to 36 VDC, 2.5 watts max

## Ordering Guide

Description	Order No.	Description	Order No.
<b>DI-710-UH USB Instrument</b> Low cost, portable, USB data logger featuring throughput rates up to 4800 Hz, 16 SE or 8 DI analog inputs and programmable gain ranges of 1, 2, 4, and 8.	DI-710-UH	<b>DI-710-EH Ethernet Instrument</b> Low cost, portable, Ethernet data logger featuring throughput rates up to 4800 Hz, 16 SE or 8 DI analog inputs and programmable gain ranges of 1, 2, 4, and 8.	DI-710-EH
<b>DI-710-UL USB Instrument</b> Same as DI-710-UH but with programmable gain ranges of 1, 10, 100, and 1000.	DI-710-UL	<b>DI-710-EL Ethernet Instrument</b> Same as DI-710-EH but with programmable gain ranges of 1, 10, 100, and 1000.	DI-710-EL
<b>DI-710-UHS USB Stand-alone Instrument</b> Same as DI-710-UH but with stand-alone capability .	DI-710-UHS	<b>DI-710-EHS Ethernet Stand-alone Instrument</b> Same as DI-710-EH but with stand-alone capability.	DI-710-EHS
<b>DI-710-ULS USB Stand-alone Instrument</b> Same as DI-710-UL but with stand-alone capability .	DI-710-ULS	<b>DI-710-ELS Ethernet Stand-alone Instrument</b> Same as DI-710-EL but with stand-alone capability.	DI-710-ELS

### Data Acquisition Product Links

(click on text to jump to page)

Data Acquisition | Data Logger | Chart Recorder | Thermocouple | Oscilloscope



241 Springside Drive  
 Akron, Ohio 44333  
 330-668-1444